


**FBT AC MX-8****AUTOMATIC MICROPHONE MIXER****Description**

The microphone automatic mixers provide great convenience to sound reinforcement installation with any size and any combination. Full feature design includes

- Daisy-chain with unlimited number of the mixer
- Three operation modes: one-channel-at-a-time, all active or override
- Switchable output levels between mic. and line level
- Individual gain control and phantom power for each channel
- Last in stays on for continuous ambience sound
- Control voltage provided to trigger external device such as a speaker switching and camera switching

The outstanding performance enables effective managing of multi-microphone installation including corporate boardrooms, conference rooms, government builds, houses of worship, classrooms

Technical data

Type	XLR
Mic	Kohm 4.7
Line	Kohm 20
OUTPUT	
Type	XLR
Mic	ohm 300
Line	ohm 200
MAX output level	dB >17
MAX gain	dB >70
Frequency response	Hz 35~20,000
THD%	<0.06%
Signal-to-noise ratio	dB >70
Input attenuation	dB -50
Phantom power	V +48
Mic In attenuation	dB -10 / -20
Mic attenuation	dB -10 / -15 / -20
Output attenuation	dB -50
Voltage output	+4VDC \pm 0.3V
Power supply	18VDC, 1A
Power consuption	W 13.5
Fuse	T0.5AE 250V (Slow-Blow)
Dimensions (WxHxD)	mm 420x44x198,5
Peso netto	Kg 2.25

D8P - 1**Extension cable****Code 37936**

- Din 8 Pin Male/Male Cable
- Lenght 0,8 m